



FEATURES



FUEL GAUGE

Fuel gauge is on the fuel tank



OHV

Over Head Valve easy to maintenance



OIL LEVEL ALARM

When the oil level is low that the engine will not start. voltage of a generator.



AVR

AVR is a device often solid state, for controlling the output



CIRCUIT PROTECTOR

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



VOLTMETER

It is a gauge for out put voltage of generator set.



CHOKE SYSTEM

When the cold weather, choke system aid to operate the engine.



DUAL ELEMENT AIR FILTER

GENERAL SPECIFICATIONS

Mono-Phase, 50 Hz, PF 1

AC Rated Power (kW)	0,90
Maximum Power (kW)	1,00
AC Rated Current	3,4
Voltage (V)	230
Frequency (Hz)	50
Phase N.	1
Power Factor	1,0
Fuel Consumption (L/h.)	0,4
Noise Level (dB(A))	66



ENGINE SPECIFICATIONS

Speed (Rpm)	3000
Oil Capacity (L)	0,4
Fuel Type	Gasoline
Fuel Tank Capacity (L.)	7,0
Start Type	Rope

DIMENSIONS AND WEIGHT

Width (mm.)	355
Lenght (mm.)	465
Height (mm.)	385
Dry Weight (kg.)	26