



## FEATURES



### **FUEL GAUGE**

Fuel gauge is on the fuel tank



### **OHV**

Over Head Valve easy to maintenance



### **OIL LEVEL ALARM**

When the oil level is low that the engine will not start. voltage of a generator.



### **AVR**

AVR is a device often solid state, for controlling the output



### **WHEEL KIT**

For easy transportation



### **CIRCUIT PROTECTOR**

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



### **VOLTMETER**

It is a gauge for out put voltage of generator set.



### **CHOKE SYSTEM**

When the cold weather, choke system aid to operate the engine.



### **DUAL ELEMENT AIR FILTER**



### **LARGE CAPACITY FUEL TANK**

15-25lt

## GENERAL SPECIFICATIONS

Mono-Phase, 50 Hz, PF 1

AC Rated Power (kW)	5 (4)
Maximum Power (kW)	5,5 (4,5)
AC Rated Current	17,3
Voltage (V)	230
Frequency (Hz)	50
Phase N.	1
Power Factor	0,80
Run Time (h)	10
Fuel Consumption (L/h.)	1,8
Noise Level (dB(A))	72



## ENGINE SPECIFICATIONS

Speed (Rpm)	3000
Power (Hp)	11
Cylinder N.	1
Cylinder Bulk	337
Fuel Type	Gasoline
Oil Capacity (L.)	1,1
Fuel Tank Capacity (L.)	25
Start Type	Rope

## DIMENSIONS AND WEIGHT

Width (mm.)	695
Lenght (mm.)	555
Height (mm.)	590
Dry Weight (kg.)	78