



FEATURES



FUEL GAUGE

Fuel gauge is on the fuel tank



OHV

Over Head Valve easy to maintenance



OIL LEVEL ALARM

When the oil level is low that the engine will not start. voltage of a generator.



AVR

AVR is a device often solid state, for controlling the output



WHEEL KIT

For easy transportation



CIRCUIT PROTECTOR

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



VOLTMETER

It is a gauge for out put voltage of generator set.



CHOKE SYSTEM

When the cold weather, choke system aid to operate the engine.



DUAL ELEMENT AIR FILTER



LARGE CAPACITY FUEL TANK

15-25lt

GENERAL SPECIFICATIONS

3 Phase, 50 Hz, PF 0.8

AC Rated Power (kW)	7,5 (6)
Maximum Power (kW)	8 (6,5)
AC Rated Current	11
DC Rated Current (A)	8
Voltage (V)	230
Frequency (Hz)	50
Phase N.	1
Power Factor	0,80
Run Time (h)	5
Fuel Consumption (L/h.)	2,8
Noise Level (dB(A))	76



ENGINE SPECIFICATIONS

Speed (Rpm)	3000
Power (Hp)	15
Cylinder N.	1
Cylinder Bulk	419
Fuel Type	Gasoline
Oil Capacity (L.)	1,1
Fuel Tank Capacity (L.)	30
Start Type	Electric

DIMENSIONS AND WEIGHT

Width (mm.)	810
Lenght (mm.)	540
Height (mm.)	575
Dry Weight (kg.)	98