



FEATURES



FUEL GAUGE

Fuel gauge is on the fuel tank



OHV

Over Head Valve easy to maintenance



OIL LEVEL ALARM

When the oil level is low that the engine will not start. voltage of a generator.



AVR

AVR is a device often solid state, for controlling the output



MAINTENANCE FREE BATTERY

It is long life



WHEEL KIT

For easy transportation



CIRCUIT PROTECTOR

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



VOLTMETER

It is a gauge for out put voltage of generator set.



GENERATOR SET OUT PUT SOCKETS



DUAL ELEMENT AIR FILTER



LARGE CAPACITY FUEL TANK

15-25lt

GENERAL SPECIFICATIONS

Mono-Phase, 50 Hz, PF 1

AC Rated Power (kW)	8,00
Maximum Power (kW)	8,80
AC Rated Current	34,80
Voltage (V)	230
Frequency (Hz)	50
Phase N.	1
Power Factor	0,80
Fuel Consumption (L/h.)	5
Run Time (Hour)	3
Noise Level (dB(A))	75,00



ENGINE SPECIFICATIONS

Speed (Rpm)	3000
Power (Hp)	18
Cylinder N.	2
Cylinder Bulk	570
Fuel Type	Gasoline
Fuel Tank Capacity (L.)	16,0
Start Type	Electric

DIMENSIONS AND WEIGHT

Width (mm.)	740
Lenght (mm.)	910
Height (mm.)	750
Dry Weight (kg.)	122