



## FEATURES



### **FUEL GAUGE**

Fuel gauge is on the fuel tank



### **OHV**

Over Head Valve easy to maintenance



### **OIL LEVEL ALARM**

voltage of a generator.



### **AVR**



### **MAINTENANCE FREE BATTERY**

It is long life



### **WHEEL KIT**

For easy transportation



### **CIRCUIT PROTECTOR**

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



### **VOLTMETER**



### **GENERATOR SET OUT PUT SOCKETS**



### **DUAL ELEMENT AIR FILTER**



### **LARGE CAPACITY FUEL TANK**

15-25lt

## GENERAL SPECIFICATIONS

3 Phase, 50 Hz, PF 0.8

AC Rated Power (kW)	10 (8,00)
Maximum Power (kW)	8,80
AC Rated Current	14,40
Voltage (V)	400
Frequency (Hz)	50
Phase N.	1
Power Factor	0,80
Fuel Consumption (L/h.)	5
Run Time (Hour)	3
Noise Level (dB(A))	75,00



## ENGINE SPECIFICATIONS

Speed (Rpm)	3000
Power (Hp)	18
Cylinder N.	2
Cylinder Bulk (mL.)	570
Fuel Type	Gasoline
Fuel Tank Capacity (L.)	16,0
Start Type	Electrical

## DIMENSIONS AND WEIGHT

Width (mm.)	740
Lenght (mm.)	910
Height (mm.)	750
Dry Weight (kg.)	122